

### MJ2955

# **PNP SILICON POWER TRANSISTORS**

The MJ2955 is a silicon Planar Epitaxial NPN transistor in Jedec TO-3 metal case. Designed for general purpose, moderate speed, switching and amplifier applications Compliance to RoHS.

Symbol	Ratings		Value	Unit
V <sub>CBO</sub>	Collector to Base Voltage		-100	V
V <sub>CEO</sub>	#Collector-Emitter Voltage		-60	V
V <sub>CER</sub>	Collector-Emitter Voltage		-70	V
V <sub>EBO</sub>	Emitter-Base Voltage		-7	V
V <sub>CB</sub>	Collector-Base Voltage		-100	V
V <sub>EB</sub>	Emitter-Base Voltage		-7	V
Ic	Collector Current – Continuous		-15	А
I <sub>B</sub>	Base Current – Continuous		-7	А
P <sub>D</sub>	Total Device Dissipation	@ T <sub>C</sub> = 25° Derate above 25°	115 0.657	W W/°C
TJ	Junction Temperature		200	°C
Ts	Storage Temperature		-65 to +200	°C

### **ABSOLUTE MAXIMUM RATINGS**

### THERMAL CHARACTERISTICS

Symbol	Ratings	Value	Unit
R <sub>thJC</sub>	Thermal Resistance, Junction to Case1.52°C/W		°C/W



## MJ2955

### **ELECTRICAL CHARACTERISTICS**

TC=25°C unless otherwise noted

Symbol	Ratings	Test Condition(s)	Min	Тур	Max	Unit
V <sub>CEO(SUS)</sub>	Collector-Emitter Sustaining Voltage (*)	I <sub>C</sub> = -200 mA, I <sub>B</sub> = 0	-60	-	-	V
V <sub>CER</sub>	Collector-Emitter Breakdown Voltage (*)	$I_{C}$ = -200 mA, $R_{BE}$ = 100 $\Omega$	-70	-	-	V
I <sub>CEO</sub>	Collector-Emitter Current	$V_{CE}$ = -30 V, I <sub>B</sub> = 0	-	-	-0.7	mA
I <sub>CEX</sub>	Collector Cutoff Current	V <sub>CE</sub> = -100 V, V <sub>EB(off)</sub> = -1.5 V	;∨		-1	
		$V_{CE}$ = -100 V, $V_{EB(off)}$ = -1.5 V T <sub>C</sub> = 150 °C	-	-	-5	mA
I <sub>EBO</sub>	Emitter Cutoff Current	$V_{BE}$ = -7 V, I <sub>C</sub> = 0	-	-	-5	mA
•	DC Current Gain	$I_{C}$ = -4 A, $V_{CE}$ = -4 A	20	-	70	
h <sub>FE</sub>		$I_{C}$ = -10 A, $V_{CE}$ = -4 A	5	-	-	-
	Collector-Emitter saturation Voltage	I <sub>C</sub> = -4 A, I <sub>B</sub> = -400 mA	-	-	-1.1	V
V <sub>CE(SAT)</sub>		I <sub>C</sub> = -10 A, I <sub>B</sub> = -3.3 A	-	-	-3	v
V <sub>BE</sub>	Base-Emitter Voltage	I <sub>C</sub> = -4 A, V <sub>CE</sub> = -4 V	-	-	-1.5	V
f <sub>T</sub>	Transition Frequency	V <sub>CE</sub> = -10 V, I <sub>C</sub> = -0.5 A f= 1 MHz	2.5	-	-	kHz
l <sub>s/b</sub>	Second Breakdown Collector Current	t= 1 S (non repetitive)	-2.87	-	-	А

In accordance with JEDEC Registration Data


(\*) Pulse Width  $\approx 300~\mu s,$  Duty Cycle  $\angle$  2.0%




### MJ2955

### **MECHANICAL DATA CASE TO-3**

DIMENSIONS (mm)		
	min max	
А	11	13.10
В	0.97	1.15
С	1.5	1.65
D	8.32	8.92
F	19	20
G	10.70	11.1
N	16.50	17.20
Р	25	26
R	4	4.09
U	38.50	39.30
V	30	30.30



Pin 1 :	Base
Pin 2 :	Emitter
Case :	Collector



#### Revised October 2014

Information furnished is believed to be accurate and reliable. However, Comset Semiconductors assumes no responsibility for the consequences of use of such information nor for any infringement of patents or other rights of third parties which may results from its use. Data are subject to change without notice. Comset Semiconductors makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Comset Semiconductors assume any liability arising out of the application or use of any product and specifically disclaims any and all liability, including without limitation consequential or incidental damages. Comset Semiconductors' products are not authorized for use as critical components in life support devices or systems.

www.comsetsemi.com

info@comsetsemi.com